

Forward Port Setting

- 1. เปิด Browser (Chrome, Firefox, IE) พิมพ์ 192.168.100.1 ในช่อง Address แล้ว∩ด Enter
- 2. ใส่ Username : root และ Password: ตรวจสอบด้านหลังอุปกรณ์ แล้วกด Log In

🥹 V163	× +	~	- ø ×
	O 🖄 192.168.100.1	☆	⊚ ⊘ ද =්
	V163		
	Welcome to Huawei web page for network c	onfiguration	
	Thereonie to Hauner theo page for hermonice	onngaration.	
	User Name :		
	Log In		

รูปที่ 1 หน[้]า login

3. KU1 Home Aan Advance > Forward Rules > IPv4 Port Mapping

٠	V163		× +							\sim		-	٥	×
\leftarrow	\rightarrow C \textcircled{a}		0 192.168.10	0.1/index.	asp				☆		(9 0	ப	=
		<u></u>	103	6 Fast Setting root = L										^
			WAN		IPv4 Port Mapping	9								
			LAN	~	On this page, you can set port to be accessed from the Intern	mapping parameters to set et.	t up virtual servers on the	LAN network and allow	these server	'S				
		+	Security	~	Note: The well-known ports for function as internal hosts.	voice services cannot be ir	n the range of the mappin	g ports. Connected APs	cannot					
		⊛ 2	Forward Rules	^	New Delete									
	1	¢	DMZ Function		Mapping Nam	e WAN Name	Internal Host	External Host	Enable					
		3	IPv4 Port Mapping		Type:	● User-defined ○ A	oplication							
			Port Trigger		Application:	Select v								
			IPv6 Port Mapping		Enable Port Mapping:									
			Application	~	WAN Name:	1 TR069 INTERN ¥			tallow these servers ed APs cannot					
					Internal Host:	*	Select v							
			WLAN	~	External Source IP			1						
			System Management	~	Address.			-						
			Maintenance Diagno.	. ~	Add			Apply	Cancel					~

รูปที่ 3 หน[้]า Forward Rules



- 4. คลิก New และทำการตั้งค่าดังนี้
 - คลิกเลือก User-defined
 - คลิกเลือก Enable Port Mapping
 - ตั้งชื่อในช่อง Mapping Name
 - เลือก WAN Name: 1_TR069_INTERNET
 - เลือก Internal Host: IP เครื่องคอมพิวเตอร์
- 5. จากนั้นคลิก **Add**

۲	V163		× +									\sim		-	٥	×
\leftarrow	\rightarrow C C		0 👌 192.168.10	🔿 👌 192.168.100.1/index.asp							5		$\overline{\mathbf{v}}$	0	பி	=
		976 v	163	0.5 Fast Setting ro								Logout				^
			WAN			IPv4 Po	rt Mapping									
			LAN	~		On this page to be access	e, you can set port map sed from the Internet.	ping parameters to set	up virtual servers on the	LAN network and allow t	hese serve	rs				
		+	Security	~		Note: The we function as it	ell-known ports for void internal hosts.	e services cannot be ir	the range of the mappin	g ports. Connected APs	cannot					
		A	Forward Rules	^	1	New	Delete									
		¢ (DMZ Function				Mapping Name	WAN Name	Internal Host	External Host	Enable					
			IPv4 Port Mapping		1	Type:	۲	User-defined OAr	plication							
			Port Trigger		2	Applicatio	Sel	ect v								
			IPv6 Port Mapping			Enable Por	rt Mapping: 🗹									
			Application	~		WAN Nam	ne: 1_1	rr069_INTERN ~								
			WLAN	~		Internal He	ost:	*	Select v							
			System Management	~		Address:				J						
			Maintenance Diagno	~	3	Add				Apply	Cancel					~

รูปที่ 4 หน[้]า IPv4 Port Mapping



6. คลิกเลือก **Protocol**:

7. ใส่ Internal port number: LAN port

8. ใส่ External port number: WAN port

9. จากนั้นคลิก **Apply**

← → C ▲ ไม่ปลอดเกีย 192.168.100.1	/index.asp			07	B e	Q	B	☆	≡ſ	-	:
	WAN		IPv4 Port Mapping								^
命	LAN	~	On this page, you can set port mapping parameters to set up virtual servers on the LAN network and allow these servers be accessed from the internet.	0							÷
Ŧ	Security	~	Note: The well-known ports for voice services cannot be in the range of the mapping ports. Connected APs cannot functio as internal hosts.	1							
\odot	Forward Rules	~	New Delete								
0	DMZ Function		Mapping Name WAN Name Internal Host External Host Enable test 1 TR069 INTERNET R VID 10 192.168.100.2 Enable								
	IPv4 Port Mapping										
	Port Trigger		Type: User-defined Application								
	IPv6 Port Mapping		Application: Select 🗸								
	Application	~	Enable Port Mapping: Mapping Name: test								
	WLAN	~	WAN Name: 1_TR069_INTER5 ~								
	System Management	~	Internal Host: 192.168.100.2 * DESKTOP-OF42F V External Source IP								
	Maintenance Diagno.		Address:								
			Protocol: TCP/UDP Internal port number: 80 - 80								
			External port number: 12000 12005 External source port								
			Delete								
			Add								
			Apply								

รูปที่ 5 หน[้]าการคลิก Apply